

**Homework 1****1) Sheet Resistance**

- a) Calculate the sheet resistance of the n+ layer if the layer depth is  $1\ \mu\text{m}$  and the doping concentration is  $2 \times 10^{25}\ \text{m}^{-3}$  (assume  $\mu_n = 2 \times 10^{-2}\ \text{m}^2/\text{Vs}$ ).
- b) Using a minimum width of  $0.9\ \mu\text{m}$ , what is the required total layer length if you are asked to implement a resistor of  $10\ \text{k}\Omega$ ?
- c) Would you be better off using the p+ layer to realize the above resistor? Explain!

**2) MOS Capacitance**

- a) Calculate the zero-bias junction capacitance between p+ diffusion and n-substrate if the substrate doping concentration is  $N_{\text{sub}} = 10^{23}\ \text{m}^{-3}$ .
- b) How much (in percent) would the junction capacitance  $C_{j0}$  change if the substrate doping concentration  $N_{\text{sub}}$  were to double?
- c) What is the total capacitance between the p+ layer and n-substrate if the diffused area measures  $1.2 \times 2.7\ \mu\text{m}^2$  and features an average depth of  $1\ \mu\text{m}$ ?

**3) MOS Transistor**

A CMOS process features substrate and well doping concentrations of  $N_A = 1 \times 10^{23}\ \text{m}^{-3}$  and  $N_D = 3 \times 10^{23}\ \text{m}^{-3}$ , respectively. Furthermore,  $\epsilon_{\text{ox}} = 3.6 \times 10^{-11}\ \text{As/Vm}$  and  $n_i = 2 \times 10^{16}\ \text{m}^{-3}$ .

- a) Determine the n-channel Fermi potential  $\phi_{Fn}$  at room temperature ( $300\ \text{K}$ ).
- b) The n-channel flat-band voltage is  $V_{FBn} = -0.6\ \text{V}$ . Calculate the gate oxide thickness  $t_{\text{ox}}$  such that  $V_{tn} = 0.8\ \text{V}$ .
- c) How much does the n-channel threshold voltage  $V_{tn}$  change if  $V_{SB} = 1\ \text{V}$ ?

## SPICE BSIM3 VERSION 3.1 PARAMETERS

```

.MODEL nfet NMOS (
+VERSION = 3.1          TNOM = 27          LEVEL = 49
+XJ = 1.5E-7           NCH = 1.7E17        TOX = 1.39E-8
+K1 = 0.8857752       K2 = -0.0935679      VTH0 = 0.6398186
+K3B = -7.6711263    W0 = 1E-8           K3 = 22.1010569
+DVT0W = 0            DVT1W = 0           NLX = 1E-9
+DVT0 = 2.7950058     DVT1 = 0.4085592    DVT2W = 0
+U0 = 453.2010286     UA = 2.494433E-13   DVT2 = -0.1237812
+UC = 2.022743E-11    VSAT = 1.730467E5    UB = 1.488658E-18
+AGS = 0.1151449     B0 = 2.792031E-6    A0 = 0.5543744
+KETA = -1.371458E-3  A1 = 0              B1 = 5E-6
+RDSW = 1.319508E3    PRWG = 0.0381943    A2 = 0.3560219
+WR = 1              WINT = 2.507126E-7  PRWB = 0.0141195
+XL = 0              XW = 0              LINT = 2.304464E-8
+DWB = 4.946821E-8    VOFF = 0            DWG = -1.755808E-8
+CIT = 0             CDSC = 2.4E-4        NFACTOR = 0.7910748
+CDSCB = 0           ETA0 = 0.0051332    CDSCD = 0
+DSUB = 0.1945608    PCLM = 2.253484     ETAB = -1.252309E-3
+PDIBLC2 = 2.440187E-3 PDIBLCB = -0.1294159 PDIBLC1 = -1
+PSCBE1 = 5.348212E8 PSCBE2 = 3.233314E-5 DROUT = 0.6751288
+DELTA = 0.01        RSH = 80.3          PVAG = 0
+PRT = 0             UTE = -1.5          MOBMOD = 1
+KT1L = 0           KT2 = 0.022         KT1 = -0.11
+UB1 = -7.61E-18    UC1 = -5.6E-11     UA1 = 4.31E-9
+WL = 0             WLN = 1            AT = 3.3E4
+WWN = 1            WWL = 0            WW = 0
+LLN = 1            LW = 0             LL = 0
+LWL = 0            CAPMOD = 2          LWN = 1
+CGDO = 2.12E-10     CGSO = 2.12E-10    XPART = 0.5
+CJ = 4.279445E-4    PB = 0.9616445     CGBO = 1E-9
+CJSW = 3.492439E-10 PBSW = 0.1          MJ = 0.4374524
+CJSWG = 1.64E-10   PBSWG = 0.1         MJSW = 0.1245165
+CF = 0             PVTH0 = 0.0431719 MJSWG = 0.1245165
+PK2 = -0.0350028   WKETA = -0.0230093 PRDSW = -30.376525
*                   LKETA = 2.090253E-3)

.MODEL pfet PMOS (
+VERSION = 3.1          TNOM = 27          LEVEL = 49
+XJ = 1.5E-7           NCH = 1.7E17        TOX = 1.39E-8
+K1 = 0.5429357       K2 = 9.433657E-3    VTH0 = -0.9488171
+K3B = -0.8567156    W0 = 1E-8           K3 = 3.2656684
+DVT0W = 0            DVT1W = 0           NLX = 1.48542E-8
+DVT0 = 2.530444     DVT1 = 0.5291909    DVT2W = 0
+U0 = 220.9301068     UA = 3.049951E-9    DVT2 = -0.1040273
+UC = -5.63429E-11    VSAT = 2E5          UB = 1E-21
+AGS = 0.1506017     B0 = 9.121548E-7    A0 = 0.9085767
+KETA = -2.819843E-3  A1 = 0              B1 = 5E-6
+RDSW = 3E3          PRWG = -0.0464229   A2 = 0.3
+WR = 1              WINT = 2.90101E-7  PRWB = -0.0398483
+XL = 0              XW = 0              LINT = 4.254314E-8
+DWB = 1.788287E-8    VOFF = -0.0659109  DWG = -2.169468E-8
+CIT = 0             CDSC = 2.4E-4        NFACTOR = 0.8188201
+CDSCB = 0           ETA0 = 1.380153E-3  CDSCD = 0
+DSUB = 0.7658995    PCLM = 2.0797597    ETAB = -0.0429727
+PDIBLC2 = 4.521707E-3 PDIBLCB = -0.0437905 PDIBLC1 = 0.1113965
+PSCBE1 = 1.25116E10 PSCBE2 = 1.227353E-9 DROUT = 0.3065171
+DELTA = 0.01        RSH = 104.9         PVAG = 8.477076E-6
+PRT = 0             UTE = -1.5          MOBMOD = 1
+KT1L = 0           KT2 = 0.022         KT1 = -0.11
+UB1 = -7.61E-18    UC1 = -5.6E-11     UA1 = 4.31E-9
+WL = 0             WLN = 1            AT = 3.3E4
+WWN = 1            WWL = 0            WW = 0
+LLN = 1            LW = 0             LL = 0
+LWL = 0            CAPMOD = 2          LWN = 1
+CGDO = 2.25E-10     CGSO = 2.25E-10    XPART = 0.5
+CJ = 7.308538E-4    PB = 0.9416073     CGBO = 1E-9
+CJSW = 2.852637E-10 PBSW = 0.99         MJ = 0.4948413
+CJSWG = 6.4E-11     PBSWG = 0.99        MJSW = 0.3001719
+CF = 0             PVTH0 = 5.98016E-3 MJSWG = 0.3001719
+PK2 = 3.73981E-3    WKETA = 4.127712E-3 PRDSW = 14.8598424
*                   LKETA = -2.567864E-3)

```